

# iDirect X1 Modem Loading Instructions


Download version IDX 3.3.6.6 from our web site at [http://www.isosat.net/download/support-files/idirect\\_support\\_files/Remote-Packages-and-iSite-IDX-3366.zip](http://www.isosat.net/download/support-files/idirect_support_files/Remote-Packages-and-iSite-IDX-3366.zip) Unzip this file into a separate folder on your desktop.

In order to log into the remote connect an Ethernet cable from your computer directly to the X1 modem's LAN port. Open a web browser and navigate to <http://IP Address> where "IP Address" is the address of your modem.

Login with the following credentials, Upper and lower case are critical for both:


User = admin

Password: P@55w0rd!




## Loading the Image and Option File –


- 1) Select "Admin" at the top of the screen




- 2) Under "Load Package" choose [Browse...] and then browse to: **Desktop > Remote Packages and iSite - iDX 3.3.6.6 > Images > Remote\_Evolution\_X1 > evo\_x1\_indoor\_rmt-15.0.6.6.pkg**




- 3) Now, choose [Load] and wait patiently until a message appears notifying you that the "Package saved successfully". Close this message.




- 4) Next under "Load Option File" choose [Browse...] and then browse to the Option File sent to you by the NOC.



- 5) Now, choose [Load] and wait patiently until a message appears notifying you that the “Options saved successfully”. Close this message.



- 6) Next under “Restart Device” click restart.



After the modem reboots, please call the NOC at 262-248-9600.