

iDirect X1 Modem Loading Instructions

Download version iDX 4.3.0.0 from our web site at

X1 Indoor: https://isotropic.network/wp-content/uploads/2024/10/evo_x1_indoor_rmt-15.0.7.5.zip


X1 Outdoor: https://isotropic.network/wp-content/uploads/2024/10/evo_x1_outdoor_rmt-15.0.7.5.zip

Unzip this file into a separate folder on your desktop. In order to log into the remote connect an Ethernet cable from your computer directly to the X1 modem's LAN port. Open a web browser and navigate to <http://IP Address> where "IP Address" is the address of your modem.

Login with the following credentials, Upper and lower case are critical for both:


User = admin

Password: P@55w0rd!




Loading the Image and Option File


- 1) Select "Admin" at the top of the screen




- 2) Under "Load Package" choose [Browse...] and then browse to: Images > Remote_Evolution_X1 > **evo_x1_indoor_rmt-15.0.7.5.pkg (X1 Indoor)** or **evo_x1_outdoor_rmt-15.0.7.5.pkg (X1 Outdoor)**




- 3) Now, choose [Load] and wait patiently until a message appears notifying you that the "Package saved successfully". Close this message.




- 4) Next under “Load Option File” choose [Browse...] and then browse to the Option File sent to you by the NOC.



- 5) Now, choose [Load] and wait patiently until a message appears notifying you that the “Options saved successfully”. Close this message.



- 6) Next under “Restart Device” click restart.



After the modem reboots, please call the NOC at 262-248-9600.